



## Mixing Amplifiers

### APPLICATIONS

- Retail stores, restaurants and bars
- BGM & Paging solutions, with message priorities and source/volume independent selection

**eHMA** series is the perfect integral solution for budget and user-friendly professional audio projects.



eHMA240



eHMA60



eHMA120

### KEY FEATURES

- Mixer + amplifier
- MIC & MIC/LINE inputs
- High & Low impedance outputs
- Auto-standby function
- Fanless, 100% silent
- Talkover function available
- 2-band tone controls for mix output
- MUTE port
- External power supply included (eHMA60 and eHMA120)

	eHMA60	eHMA120	eHMA240
1 channel @ 4Ω (RMS)	66W	95W	250W
1 channel @ 70/100V(RMS)	60W	95W	245W
Inputs	2 MIC/LINE + 1 MIC	2 MIC/LINE + 1 MIC + 1 LINE	2 MIC/LINE + 2 MIC + 2 LINE
Outputs	1 Hi-Z + 1 Lo-Z	2 Hi-Z + 1 Lo-Z + 1 AUX/REC	4 Hi-Z + 1 Lo-Z + 1 AUX/REC
Dimensions / Weight	1RU x 150mm depth / 1,9 kg.	1RU x 120mm depth / 2,9 kg.	2RU x 341mm depth / 6,5 kg.

### ACCESSORIES

eHMA60/ eHMA120:

- 1UHRMKIT

eHMA240:

- 2UHRMKIT

